

intercable

Intersection	Standard Cable Lugs R-series	Instructions for use for making a good connection with Intercable products R-series
mm ²	5 mm crimp inserts i-crimping	
6	1	Strip the conductor on the length of the tube length where you remove an extra 10% because the length of the cable shoe can become slightly longer during pressing.
10	1	
16	2	
25	2	
35	2	
50	2	
70	2	
95	2	
120	3	
150	3	
185	3	
240	4	
300	4	
		<p>Clean the conductor before mounting.</p> <p>Insert the guide completely to the end of the cable shoe.</p> <p>Start with the first pressing on the flag or eye side of the cable shoe.</p> <p>this way, the length change will move backwards.</p>

COPPER

English

